

### RF Wall mount Dimmer



- RF Wireless remote
- On/off: Dim up & Down
- Magnetic housing
- Battery operated



**Mounting:** Screws or Magnet  
**Recessed Cutout:** 1-3/8" (35mm)



- Receiver operates 12-36V DC
- Dims puck lights, linear lights, flexible strip lights etc
- Surface mountable

|                   |   |
|-------------------|---|
| Product Code      | LS-RF-DIM-MWM<br>LS-WM-DIM-REC  |
| Input Voltage     | 12 - 36V DC   |
| Max Load          | 8 Amps  |
| Output            | Single Channel  |
| Output Power      | (12v=96W / 24V=192W)  |
| Receiver Size     | L3 <sup>47/64</sup> x W1 <sup>29/64</sup> x H0.79"<br>L95 x W37 x H20mm   |
| Remote Size       | Ø1 <sup>1/2</sup> " (38.5mm)  |
| Cutout for remote | Ø1 <sup>3/8</sup> " (35mm)  |
| Remote Function   | On/off & Dimming<br>Press button to dim up or down<br><br><b>Mounting - 3 Ways</b><br>Surface / Magnet / Recessed |

## Applications

Under cabinet lights  
 Flexible strip lights  
 Display lighting

## Features

- RF Dimmer Remote/Receiver options
- Used with 12V or 24V systems
- Requires no additional wiring
- One dimmer can handle up to 96W
- Controls dimmer up to 30ft away

**3 Year Warranty**

### Dimensions

