

Date: _____ Project: _____

Notes: _____



RECESSED PIR MOTION SENSOR

Recessed motion sensor, 10' radius to activate.

Features

- Uses passive infrared sensor to turn low voltage LED lighting on/off
- 3M (10') sensor range
- On time - 40 seconds

Applications

Cabinets | Drawers | Closets

Installation

Recessed, 15/32 to 1/2" (11 to 12.8mm) hole cutout

Code	LS-MS-PIR	
Input Voltage	12V DC	24V DC
Output Power	30W	60W
Output Current	1x2.5A/Channel	
Wire Size	2 Wire (+/-) 22AWG	
Working Temp	-24°C~60°C (-10°F~140°F)	

Dimensions

L3^{1/2} x W2^{21/64} x H1^{3/8}" (L89 x W59 x H35mm)



RECESSED ON/OFF SWITCH

Touch or motion hand 0.6" in front to turn on or off.

Features

- Uses passive infrared sensor to turn low voltage LED lighting on/off
- 3M (10') sensor range

Applications

Cabinets | Drawers | Closets

Installation

Recessed, 15/32 to 1/2" (11 to 12.8mm) hole cutout

Code	LS-SNS-SW	
Input Voltage	12V DC	24V DC
Output Power	30W	60W
Output Current	1x2.5A/Channel	
Wire Size	2 Wire (+/-) 22AWG	
Working Temp	-24°C~60°C (-10°F~140°F)	

Dimensions

L3^{1/2} x W2^{21/64} x H1^{3/8}" (L89 x W59 x H35mm)